2967293

https://www.phoenixcontact.com/in/products/2967293

PHŒNIX CONTACT

Please be informed that the data shown in this PDF document is generated from our Online Catalog. Please find the complete data in the user documentation. Our General Terms of Use for Downloads are valid.



PLC-INTERFACE, consisting of basic terminal block PLC-BSC.../21 with screw connection and plug-in miniature relay with power contact, for assembly on DIN rail NS 35/7,5, 2 changeover contacts, input voltage 60 V DC

Your advantages

- Slim design
- · Efficient connection to system cabling using V8 adapter
- · RT III sealed relay
- · Safe isolation according to DIN EN 50178 between coil and contact
- · Integrated input circuit and interference suppression circuit
- Functional plug-in bridges

Commercial Data

Item number	2967293
Packing unit	10 pc
Minimum order quantity	1 pc
Sales Key	CK6
Product Key	CK621C
Catalog Page	Page 366 (C-5-2019)
GTIN	4017918164072
Weight per Piece (including packing)	76.49 g
Weight per Piece (excluding packing)	67.9 g
Customs tariff number	85364900
Country of origin	DE



https://www.phoenixcontact.com/in/products/2967293

Technical Data

Product properties

Product type	Relay Module
Product family	PLC-INTERFACE
Application	Universal
Operating mode	100% operating factor
Mechanical service life	3x 10 ⁷ cycles
Insulation characteristics	Sofa isolation: Control side / contact side
Insulation	Safe isolation: Control side / contact side
Insulation characteristics	
Insulation	Safe isolation: Control side / contact side
Overvoltage category	III
Pollution degree	3

Electrical properties

Maximum power dissipation for nominal condition	0.6 W
Test voltage (Winding/contact)	4 kV AC (50 Hz, 1 min., winding/contact)
Test voltage (Changeover contact/changeover contact)	2.5 kV AC (50 Hz, 1 min., changeover contact/changeover contact)
Rated surge voltage	6 kV

Input data

Coil side	
Nominal input voltage U _N	60 V DC
Input voltage range	51 V DC 84 V DC (20 °C)
Drive and function	monostable
Drive (polarity)	polarized
Typical input current at U _N	10 mA
Typical response time	8 ms
Typical release time	10 ms
Protective circuit	Reverse polarity protection; Polarity protection diode
	Freewheeling diode; Freewheeling diode
Operating voltage display	yes

Output data

Switching

Contact switching type	2 changeover contacts
Type of switch contact	Single contact
Contact material	AgNi
Maximum switching voltage	250 V AC/DC (The separating plate PLC-ATP should be installed for voltages larger than 250 V (L1, L2, L3) between identical

PHŒNIX CONTACT



2967293

https://www.phoenixcontact.com/in/products/2967293

	terminal blocks in adjacent modules. Potential bridging is then carried out with FBST 8-PLC orFBST 500)
Minimum switching voltage	5 V AC/DC (10 mA)
Limiting continuous current	6 A
Maximum inrush current	15 A (300 ms)
Min. switching current	10 mA (5 V)
Interrupting rating (ohmic load) max.	140 W (at 24 V DC)
	85 W (at 48 V DC)
	60 W (at 60 V DC)
	44 W (at 110 V DC)
	60 W (at 220 V DC)
	1500 VA (for 250 V AC)
Switching capacity	2 A (at 24 V, DC13)
	3 A (at 24 V, AC15)
	3 A (at 120 V, AC15)
	0.2 A (at 250 V, DC13)
	3 A (at 250 V, AC15)

Connection data

Connection method	Screw connection
Stripping length	8 mm
Screw thread	M3
Conductor cross section rigid	0.14 mm ² 2.5 mm ²
Conductor cross section flexible	0.14 mm ² 2.5 mm ²
	0.2 mm ² 2.5 mm ² (Single ferrule)
	2x 0.5 mm ² 1.5 mm ² (TWIN ferrule)
Conductor cross section AWG	26 14
Tightening torque	0.6 Nm 0.8 Nm

Dimensions

Width	14 mm
Height	80 mm
Depth	94 mm

Material specifications

Flammability rating according to UL 94 V0	0 (Housing)
---	-------------

Environmental and real-life conditions

Degree of protection (Relay)	RT III (Relay)
Degree of protection (Relay base)	IP20 (Relay base)
Ambient temperature (operation)	-40 °C 60 °C
Ambient temperature (storage/transport)	-40 °C 85 °C



https://www.phoenixcontact.com/in/products/2967293



Approvals

Corrosive gas test	
Identification	ISA-S71.04. G3 Harsh Group
	EN 60068-2-60
Standards and regulations	
Standards/regulations	IEC 60947-5-1
Mounting	
Mounting type	DIN rail mounting
Assembly instructions	in rows with zero spacing
Mounting position	any

Phoenix Contact 2023 © - all rights reserved https://www.phoenixcontact.com

PHOENIX CONTACT (I) Pvt. Ltd. A-58/2, Okhla Industrial Area, Phase - II, New Delhi-110 020

+91.1275.71420 info@phoenixcontact.co.in